



Features :

- Constant voltage design
- Universal AC input / Full range
- Protections: Short circuit / Over load / Over voltage
- Fully isolated plastic case
- Cooling by free air convection
- · Small and compact size
- Class ${\rm II}$ power unit, no FG
- · Class 2 power unit
- Pass LPS
- IP30 design
- Suitable for LED lighting and moving sign applications
- 100% full load burn-in test
- · Low cost, high reliability
- 2 years warranty

P F 110 SELV II LPS IP30 C TO CB (6 (Note 2)

| SPECIFIC | ATION | | y year en LPS | JII JO G TO JE | LIT CBCE (Note.8 | |
|-----------------|---|--|---------------|----------------|------------------|--|
| MODEL | | APV-16-5 | APV-16-12 | APV-16-15 | APV-16-24 | |
| OUTPUT | DC VOLTAGE | 5V | 12V | 15V | 24V | |
| | RATED CURRENT | 2.6A | 1.25A | 1A | 0.67A | |
| | CURRENT RANGE | 0 ~ 2.6A | 0 ~ 1.25A | 0 ~ 1A | 0 ~ 0.67A | |
| | RATED POWER | 13W | 15W | 15W | 16.08W | |
| | RIPPLE & NOISE (max.) Note.2 | 100mVp-p | 120mVp-p | 120mVp-p | 150mVp-p | |
| | VOLTAGE TOLERANCE Note.3 | ±5.0% | | | | |
| | LINE REGULATION | ±1.0% | | | | |
| | LOAD REGULATION | ±2.0% | | | | |
| | SETUP, RISE TIME Note.6 | 1500ms, 30ms / 230VAC 1500ms, 30ms / 115VAC at full load | | | | |
| | HOLD UP TIME (Typ.) | 20ms/230VAC 12ms/115VAC at full load | | | | |
| | VOLTAGE RANGE Note.4 | 90 ~ 264VAC 127 ~ 370VDC | | | | |
| INPUT | FREQUENCY RANGE | 47 ~ 63Hz | | | | |
| | EFFICIENCY (Typ.) | 76% | 80% | 81% | 83% | |
| | AC CURRENT | 0.3A/230VAC 0.5A/115VAC | | | | |
| | INRUSH CURRENT(Typ.) | COLD START 50A(twidth=185μs measured at 50% Ipeak) at 230VAC | | | | |
| | LEAKAGE CURRENT | 0.25mA / 240VAC | | | | |
| PROTECTION | OVER LOAD | Above 105% rated output power | | | | |
| | OVERLOAD | Protection type: Hiccup mode, recovers automatically after fault condition is removed | | | | |
| | OVED VOLTACE | 5.75 ~ 6.75V | 13.8 ~ 16V | 17.5 ~ 21V | 27.6 ~ 32.4V | |
| | OVER VOLTAGE | Protection type : Shut off o/p voltage, clamping by zener diode | | | | |
| ENVIRONMENT | WORKING TEMP. | -30 ~ +70°C (Refer to "Derating Curve") | | | | |
| | WORKING HUMIDITY | 20 ~ 90% RH non-condensing | | | | |
| | STORAGE TEMP., HUMIDITY | -40 ~ +80°C, 10 ~ 95% RH | | | | |
| | TEMP. COEFFICIENT | ±0.03%/°C (0 ~ 50°C) | | | | |
| | VIBRATION | 10 ~ 500Hz, 2G 10min./1cycle, period for 60min. each along X, Y, Z axes | | | | |
| SAFETY & EMC | SAFETY STANDARDS | UL8750,CSA C22.2 No.250.0-08, ENEC EN61347-1,EN61347-2-13,EN62384 Independent,IP30 Approved | | | | |
| | WITHSTAND VOLTAGE | I/P-O/P:3.75KVAC | | | | |
| | ISOLATION RESISTANCE | I/P-O/P:>100M Ohms / 500VDC / 25°C / 70% RH | | | | |
| | EMC EMISSION | Compliance to EN55015,EN61000-3-2 Class A,EN61000-3-3 | | | | |
| | EMC IMMUNITY | Compliance to EN61547,EN61000-4-2,3,4,5,6,8,11; light industry level(surge 2KV), criteria A | | | | |
| OTHERS | MTBF | 1145.7K hrs min. MIL-HDBK-217F (25°C) | | | | |
| | DIMENSION | 77*40*29mm (L*W*H) | | | | |
| | PACKING | 0.1Kg; 120pcs/14Kg/1.06CUFT | • | | | |
| NOTE | Ripple & noise are measure Tolerance : includes set up Derating may be needed ur The power supply is consid complete installation, the fir Length of set up time is me The unit might not be suital | rameters NOT specially mentioned are measured at 230VAC input, rated load and 25°C of ambient temperature. e & noise are measured at 20MHz of bandwidth by using a 12" twisted pair-wire terminated with a 0.1uf & 47uf parallel capacitor. ance: includes set up tolerance, line regulation and load regulation. ling may be needed under low input voltage. Please check the static characteristics for more details. lower supply is considered as a component that will be operated in combination with final equipment. Since EMC performance will be affected by the lete installation, the final equipment manufacturers must re-qualify EMC Directive on the complete installation again. In of set up time is measured at first cold start. Turning ON/OFF the power supply may lead to increase of the set up time. In might not be suitable for lighting applications in EU countries. Please check with your local authorities for the possible use of the unit. fill requirements of the latest ErP regulation for lighting fixtures, this LED power supply can only be used behind a switch without permanently nected to the mains. | | | | |



